

# FQP7N80C/FQPF7N80C

## 800V N-Channel MOSFET

### **General Description**

These N-Channel enhancement mode power field effect transistors are produced using Fairchild's proprietary, planar stripe, DMOS technology.


This advanced technology has been especially tailored to minimize on-state resistance, provide superior switching performance, and withstand high energy pulse in the avalanche and commutation mode. These devices are well suited for high efficiency switch mode power supplies.

### **Features**

- 6.6A, 800V,  $R_{DS(on)} = 1.9\Omega \ @V_{GS} = 10 \ V$  Low gate charge ( typical 27 nC)
- Low Crss (typical 10 pF)
- Fast switching
- 100% avalanche tested
- · Improved dv/dt capability







# Absolute Maximum Ratings T<sub>C</sub> = 25°C unless otherwise noted

Symbol	Parameter		FQP7N80C	FQPF7N80C	Units
$V_{DSS}$	Drain-Source Voltage		800		V
I <sub>D</sub>	Drain Current - Continuous (T <sub>C</sub> = 25°C)		6.6	6.6 *	Α
	- Continuous (T <sub>C</sub> = 100°C)		4.2	4.2 *	Α
I <sub>DM</sub>	Drain Current - Pulsed	(Note 1)	26.4	26.4 *	Α
$V_{GSS}$	Gate-Source Voltage		± 30		V
E <sub>AS</sub>	Single Pulsed Avalanche Energy (Note		580		mJ
I <sub>AR</sub>	Avalanche Current	(Note 1)	6	.6	Α
E <sub>AR</sub>	Repetitive Avalanche Energy (Note 1)		16.7		mJ
dv/dt	Peak Diode Recovery dv/dt (Note 3)		4.5		V/ns
$P_D$	Power Dissipation (T <sub>C</sub> = 25°C)		167	56	W
	- Derate above 25°C		1.33	0.44	W/°C
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Temperature Range		-55 to +150		°C
T <sub>I</sub>	Maximum lead temperature for soldering pur	ooses,	300		°C
L	1/8" from case for 5 seconds				

<sup>\*</sup> Drain current limited by maximum junction temperature.

### **Thermal Characteristics**

Symbol	Parameter	FQP7N80C	FQPF7N80C	Units
$R_{\theta JC}$	Thermal Resistance, Junction-to-Case	0.75	2.25	°C/W
$R_{\theta JS}$	Thermal Resistance, Case-to-Sink Typ.	0.5		°C/W
$R_{\theta JA}$	Thermal Resistance, Junction-to-Ambient	62.5	62.5	°C/W

Symbol	Parameter	Test Conditions	N	/lin	Тур	Max	Units
Off Cha	aracteristics						
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	$V_{GS} = 0 \text{ V}, I_{D} = 250 \mu\text{A}$	8	00			V
ΔBV <sub>DSS</sub> / ΔΤ <sub>J</sub>	Breakdown Voltage Temperature Coefficient	$I_D = 250 \mu A$ , Referenced to	25°C		0.93		V/°C
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	V <sub>DS</sub> = 800 V, V <sub>GS</sub> = 0 V				10	μΑ
		V <sub>DS</sub> = 640 V, T <sub>C</sub> = 125°C				100	μΑ
I <sub>GSSF</sub>	Gate-Body Leakage Current, Forward	$V_{GS} = 30 \text{ V}, V_{DS} = 0 \text{ V}$				100	nA
I <sub>GSSR</sub>	Gate-Body Leakage Current, Reverse	$V_{GS} = -30 \text{ V}, V_{DS} = 0 \text{ V}$				-100	nA
On Cha	racteristics						
V <sub>GS(th)</sub>	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu\text{A}$	3	3.0		5.0	V
R <sub>DS(on)</sub>	Static Drain-Source On-Resistance	V <sub>GS</sub> = 10 V, I <sub>D</sub> = 3.3 A			1.57	1.9	Ω
9 <sub>FS</sub>	Forward Transconductance	$V_{DS} = 50 \text{ V}, I_D = 3.3 \text{ A}$	Note 4)		5.5		S
C <sub>iss</sub>	ic Characteristics Input Capacitance Output Capacitance	$V_{DS} = 25 \text{ V}, V_{GS} = 0 \text{ V},$ $f = 1.0 \text{ MHz}$			1290 120	1680 155	pF pF
	' '				120	155	pF
C <sub>rss</sub>	Reverse Transfer Capacitance				10	13	pF
Switchi	ing Characteristics						
t <sub>d(on)</sub>	Turn-On Delay Time	$V_{DD} = 400 \text{ V}, I_{D} = 6.6 \text{ A},$ $R_{G} = 25 \Omega$			35	80	ns
t <sub>r</sub>	Turn-On Rise Time				100	210	ns
t <sub>d(off)</sub>	Turn-Off Delay Time				50	110	ns
t <sub>f</sub>	Turn-Off Fall Time	(No	ote 4, 5)		60	130	ns
Qg	Total Gate Charge	$V_{DS} = 640 \text{ V}, I_D = 6.6 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5)			27	35	nC
Q <sub>gs</sub>	Gate-Source Charge				8.2		nC
Q <sub>gd</sub>	Gate-Drain Charge				11		nC
	ource Diode Characteristics a						
I <sub>S</sub>	Maximum Continuous Drain-Source Diode Forward Current					6.6	A
I <sub>SM</sub>	Maximum Pulsed Drain-Source Diode F					26.4	A
V <sub>SD</sub>	Drain-Source Diode Forward Voltage	$V_{GS} = 0 \text{ V}, I_{S} = 6.6 \text{ A}$				1.4	V
t <sub>rr</sub>	Reverse Recovery Time	$V_{GS} = 0 \text{ V}, I_{S} = 6.6 \text{ A},$			650		ns
$Q_{rr}$	Reverse Recovery Charge	$dI_F / dt = 100 A/\mu s $	Note 4)		7.0		μC

- Notes: 
  1. Repetitive Rating : Pulse width limited by maximum junction temperature 2. L = 25mH, I<sub>AS</sub> = 6.6A, V<sub>DD</sub> = 50V, R<sub>G</sub> = 25 Ω, Starting T<sub>J</sub> = 25°C 3. I<sub>SD</sub> ≤ 8A, di/dt ≤ 200A/μs, V<sub>DD</sub> ≤ BV<sub>DSS</sub>, Starting T<sub>J</sub> = 25°C 4. Pulse Test : Pulse width ≤ 300μs, Duty cycle ≤ 2% 5. Essentially independent of operating temperature

# **Typical Characteristics**




Figure 1. On-Region Characteristics




Figure 2. Transfer Characteristics




Figure 3. On-Resistance Variation vs Drain Current and Gate Voltage




Figure 4. Body Diode Forward Voltage Variation with Source Current and Temperature




Figure 5. Capacitance Characteristics




Figure 6. Gate Charge Characteristics

©2003 Fairchild Semiconductor Corporation Rev. A, April 2003

# **Typical Characteristics** (Continued)




Figure 7. Breakdown Voltage Variation vs Temperature




Figure 8. On-Resistance Variation vs Temperature




Figure 9-1. Maximum Safe Operating Area for FQP7N80C




Figure 9-2. Maximum Safe Operating Area for FQPF7N80C




Figure 10. Maximum Drain Current vs Case Temperature

# Typical Characteristics (Continued)




Figure 11-1. Transient Thermal Response Curve for FQP7N80C






Figure 11-2. Transient Thermal Response Curve for FQPF7N80C

©2003 Fairchild Semiconductor Corporation Rev. A, April 2003


# **Gate Charge Test Circuit & Waveform**




## **Resistive Switching Test Circuit & Waveforms**





## **Unclamped Inductive Switching Test Circuit & Waveforms**




### Peak Diode Recovery dv/dt Test Circuit & Waveforms









Body Diode Reverse Current



©2003 Fairchild Semiconductor Corporation





#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FACT™	ImpliedDisconnect™	PACMAN™	SPM™
ActiveArray™	FACT Quiet series™	ISOPLANAR™	POP™	Stealth™
Bottomless™	FAST <sup>®</sup>	LittleFET™	Power247™	SuperSOT™-3
CoolFET™	FASTr™	MicroFET™	PowerTrench <sup>®</sup>	SuperSOT™-6
$CROSSVOLT^{TM}$	FRFET™	MicroPak™	QFET™	SuperSOT™-8
DOME™	GlobalOptoisolator™	MICROWIRE™	QS <sup>TM</sup>	SyncFET™
EcoSPARK™	GTO™	MSX™	QT Optoelectronics™	TinyLogic <sup>®</sup>
E <sup>2</sup> CMOS™	HiSeC™	MSXPro™	Quiet Series™	TruTranslation™
EnSigna™	$I^2C^{TM}$	$OCX^{TM}$	RapidConfigure™	UHC™
Across the board.	Around the world.™	OCXPro™	RapidConnect™	UltraFET <sup>®</sup>
The Power Franc	hise™	OPTOLOGIC <sup>®</sup>	SILENT SWITCHER®	$VCX^{TM}$
Programmable Active Droop™		OPTOPLANAR™	SMART START™	

#### **DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### PRODUCT STATUS DEFINITIONS

### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2003 Fairchild Semiconductor Corporation Rev. I2